

- Economically priced general purpose soldering iron.
- Compact and lightweight design for easy handling.
- Available with Long-life tip or Nickel plated conventional copper tip.



**KX-30R**

Model / Application		IC	P.C. Board	Transistors	Condensers	Resistors	Switches	Terminals	Connectors	Lead wires	Coaxial Cables	Metal Crases
KX-20/20R	20W	○	○	○	○	—	—	○	—	—	—	—
KX-30/30R	30W	○	○	○	○	○	○	○	—	—	—	—
KX-40/40R	40W	—	○	○	○	○	○	○	—	—	—	—
KX-60/60R	60W	—	—	—	○	○	○	○	—	—	—	—
KX-80/80R	80W	—	—	—	—	○	○	○	○	○	○	○
KX-100/100R	100W	—	—	—	—	○	○	○	○	○	○	○

○ The most suitable ○ Suitable — Not suitable

**With Copper Tip**

Model	KX-20	KX-30	KX-40	KX-60	KX-80	KX-100
Voltage	110, 120, 130, 220, 230V AC 50/60Hz					
Power Consumption	20W	30W	40W	60W	80W	100W
Length	*208mm			*233mm	*238mm	*243mm
Weight	*50g			*70g	*75g	*80g

**With Long Life Tip**

Model	KX-20R	KX-30R	KX-40R	KX-60R	KX-80R	KX-100R
Voltage	110, 120, 130, 220V AC 50/60Hz					
Power Consumption	20W	30W	40W	60W	80W	100W
Length	*208mm			*233mm	*238mm	*243mm
Weight	*50g			*70g	*75g	*80g

\*Without cord bushing  
\*Without cord

**Replacement Parts**

- ☑ KX-20R Heater **KS-20H**
- ☑ KX-30R Heater **KS-30H**
- ☑ KX-40R Heater **KS-40H**
- ☑ KX-60R Heater **KS-60H**
- ☑ KX-80R Heater **KS-80H**
- ☑ KX-100R Heater **KS-100H**

**Standard Tip**

KX-20R	R-48SB	KX-20	T-48B
KX-30R	R-48B	KX-30	T-48B
KX-40R	R-48B	KX-40	T-48B
KX-60R	R-6BC	KX-60	T-6B
KX-80R	RD-67BC	KX-80	TD-67B
KX-100R	RD-68BC	KX-100	TD-68B

**Replacement Tips**

